

DIE SELECTION GUIDE FOR B35-50MDE

Copper Tube Connectors

| Copper Conductor sqmm Low str. Flex. | | Connector | | Hexagonal Crimp | | Indent Crimp | | |
|--|-----|------------------|-------------------|-----------------|----------------|--------------|----------|----------------|
| | | Terminal Lug | Through Connector | Die Set | No. of Crimps* | Nest | Indentor | No. of Crimps* |
| 4 - 6 | | A1-M | L1-M | ME1-50 | 1 | MA1-50 | PA1-50 | 1 |
| 10 | | A2-M A2-P12 | L2-M | ME2-50 | 1 | MA2.3-50 | PA5-50 | 1 |
| 16 | | A3-M A3-P14 | L3-M | ME3-50 | 1 | | | 1 |
| 25 | | A5-M A5-P16 | L5-M | ME5-50 | 1 | MA5-50 | | 1 |
| 35 | 25 | A7-M A7-P20 | L7-M | ME7-50 | 1 | MA7-50 | PA10-50 | 1 |
| | 35 | | | | | MA9-50 | | 1 |
| | 35 | A9-M | | ME9-50 | 1 | MA9-50 | | 1 |
| 50 | 50 | A10-M A10-P25 | L10-M | ME10-50 | 2 | MA10-50 | | 1 |
| | | | | | | 50 | A12-M | |
| 70 | 70 | A14-M A14-P30 | L14-M | ME14-50 | 2 | MA14-50 | PA19-50 | 1 |
| | | | | | | 70 | | A17-M |
| | 70 | A19-M | L19-M | ME19-50 | 2 | MA19-50 | | 1 |
| 95 | 95 | A20-M | | ME20-50 | 2 | MA20-50 | 1 | |
| 120 | 120 | A24-M | L24-M | ME24L-50 | 2 | MA24-50 | PA24-50 | 1 |
| | | 120 | A29-M | | ME29-50 | 3 | | |
| 150 | 150 | A30-M | L30-M | ME30L-50 | 3 | | | |

* No. of Crimps per end for Through Connectors

Further assistance from Cembre Ltd
Tel: 01675 470440 Fax: 01675 470220 E-mail: sales@cembre.co.uk