

DIE SELECTION GUIDE FOR HT131-C

Also applicable for

HT120, HT131LN-C, HT131-UC, RHC131, RHC131LN, RHU131-C, RHM132**,

B1300-CE, B1300-CE-KV, B1300L-CE, B1300-UCE, B1350-CE, B1350-CE-KV, B1350L-CE & B1350-UCE

Copper Tube Connectors

Copper Conductor sqmm Low Str. Flex.		Connector		Hexagonal Crimp		Indent Crimp			
		Terminal Lug	Through Connector	Die Set	No. of Crimps*	Nest	Indentor	No. of Crimps*	
4 - 6		A1-M	L1-M						
10		A2-M A2-P12	L2-M	ME2-C	1	MA2-C	PA10-C	1	
16		A3-M A3-P14	L3-M	ME3-C	1	MA3-C			
25		A5-M A5-P16	L5-M	ME5-C	1	MA5-C			
35	25 35	A7-M A7-P20	L7-M	ME7-C	1	MA7-C			
	35	A9-M		ME9-C	1	MA9-C			
50	50	A10-M A10-P25	L10-M	ME10-C	1	MA10-C			
	50	A12-M		ME12-C	1	MA12-C	PA24-C	1	
70	70	A14-M A14-P30	L14-M	ME14-C	1	MA14-C			
	70	A17-M		ME17-C	1	MA17-C			
95	95	A19-M	L19-M	ME19-C	1	MA19-C			
	95	A20-M		ME20-C	1	MA20-C			
120	120	A24-M	L24-M	ME24-C	1	MA24-C			
	120	A29-M		ME29-C	1	MA29-C	PA48-C	1	
150	150	A30-M	L30-M	ME30-C	1	MA30-C			
	150	A35-M		ME35-C	1	MA35-C			
185	185	A37-M	L37-M	ME37-C	1	MA37-C			
	185	A40-M		ME40-C	1	MA40-C			
240	240	A48-M	L48-M	ME48-C	2	MA48-C			
300	240 300	A60-M A60-4ESI	L60-M	ME60-C	3	MA60-C	PA60-C	1	
400	300	A80-M A80-4ESI	L80-M	ME80-C	3				

* No. of Crimps per end for Through Connectors

** Not suitable for Through Connectors

Further assistance from Cembre Ltd

Tel: 01675 470440 Fax: 01675 470220 E-mail: sales@cembre.co.uk