

## DIE SELECTION GUIDE FOR HT131-C

Also applicable for

HT120, HT131LN-C, HT131-UC, RHC131, RHC131LN, RHU131-C, RHM132\*\*,

B1300-CE, B1300-CE-KV, B1300L-CE, B1300-UCE, B1350-CE, B1350-CE-KV, B1350L-CE & B1350-UCE

### Heavy Duty Copper Tube Terminals

Copper Conductor sqmm		Terminal Lug	Hexagonal Crimp	
Low Str.	Flex.		Die Set	No. of Crimps
16		2A3-M	ME3-C	2
25		2A5-M	ME5-C	2
35	25 35	2A7-M	ME7-C	2
50	35 - 50	2A10-M	ME10-C	2
70	50 - 70	2A14-M	ME14-C	2
95	70 - 95	2A19-M	ME19-C	2
120	95 - 120	2A24-M	ME24-C	3
150	120 - 150	2A30-M	ME30-C	3
185	150 - 185	2A37-M	ME37-C	3
240	185 - 240	2A48-M	ME48-C	3
300	240 - 300	2A60-M	ME60-C	5
400	300	2A80-M	ME80-C	6

### Terminal lugs and Through Connectors according to DIN46235 and DIN46267 Pt 1

Copper Conductor sqmm	Connector		Hexagonal Crimp	
	Terminal Lug	Through Connector	Die Set	No. of Crimps*
6	DR6-..	DSV6	MK5-C	1
10	DR10-..	DSV10	MK6-C	1
16	DR16-..	DSV16	MK8-C	1
25	DR25-..	DSV25	MK10-C	1
35	DR35-..	DSV35	MK12-C	1
50	DR50-..	DSV50	MK14-C	1
70	DR70-..	DSV70	MK16-C	1
95	DR95-..	DSV95	MK18-C	2
120	DR120-..	DSV120	MK20-C	2
150	DR150-..	DSV150	MK22-C	2
185	DR185-..	DSV185	MK25-C	2
240	DR240-..	DSV240	MK28-C	2
300	DR300-..	DSV300	MK32-C	5

\* No. of Crimps per end for Through Connectors \*\* Not suitable for Through Connectors

Further assistance from Cembre Ltd

Tel: 01675 470440 Fax: 01675 470220 E-mail: sales@cembre.co.uk