



TIS 1005 Socket & RCD Tester



The TIS 1005 is a pocket sized checker for indicating loop impedance, socket polarity and RCD 30mA are all ok. Indication is by LED's and buzzer. It is an ideal unit for initial "checking out" of a 13A socket and will advise if the circuit is ok, needs attention, or needs urgent attention. An ideal product for housing associations, landlords, council property departments, shopping centres, electricians etc.

Specification

Basic Functions

Nominal Voltage: 230V AC \pm 10%, 110V AC \pm 10%
Frequency Range: 50Hz - 60Hz
Contact Voltage Range: <50V AC (Relative to Ground)
Overload Protection: AC/DC 300V

Special Functions

Earth Loop Check at mains frequency
Checks condition of Earth Loop
Loop Detection Ranges <1.8 Ω , 1.8 Ω - 92 Ω , >92 Ω
30mA RCD Test
3 Coloured LED's (Green, Amber, Red) give indication of condition
Socket checked against all possible fault conditions
Microprocessor controlled with built in self check
First Socket Tester to indicate actual fault - Live, Neutral or Earth
Simple and easy to use
Plug in and switch on

General Characteristics

Weight: 40g
Size: 72mm x 78mm x 80mm
CE Approved
2 Year Guarantee