

Order Code: XCBT2X1
BATTEN X1 CCT [3000K/4000K/6000K] + Wattage Switchable



Features

- Ideal for replacement of linear fluorescent fixtures
- Suitable for general domestic and commercial use
- CCT [3000K/4000K/6000K] adjustable via simple 3-way selector switch
- Wattage [11 to 18] adjustable via 2-way dip switch

Construction

- Steel body in white finish
- High quality opal diffuser to reduce glare
- Integral emergency option available
- Loop in/out mains connector
- BESA fixings for rear or end cable entry



Technical Data

General	
Luminaire Wattage (W)	11 to 18
Weight (kg)	0.68
Operating Temperature (ta °C)	45
Light Output	
Lumens (lm)	1300 to 2300
Efficacy (lm/W)	132
LED	
CRI	85
Macadam Ellipses	5
Driver	
Driver Current (mA)	200 , 250 , 300 , 350
Forward Voltage (V)	25 to 57
Emergency	
Emergency Lumen Operating	264
Emergency Wattage (W)	2

Electrical	
Rated Input Current (A)	0.09
Power Factor (pf)	0.83 to 0.92
Input Voltage Range (VAC)	220 to 240
Inrush Current Peak (A)	175
Surge Protection (kV)	L-N 1kV, LN-PG 2kV
Conductor Size (mm)	0.5 to 2.5
Terminal Type	3 pole piano key

Order Code: XCBT2X1

BATTEN X1 CCT [3000K/4000K/6000K] + Wattage Switchable

Dimensions

A (mm)	600
B (mm)	55
C (mm)	58

Line Drawing

