

Order Code: XCBT5X1
BATTEN X1 CCT [3000K/4000K/6000K] + Wattage Switchable



Features

- Ideal for replacement of linear fluorescent fixtures
- Suitable for general domestic and commercial use
- CCT [3000K/4000K/6000K] adjustable via simple 3-way selector switch
- Wattage [31 to 57] adjustable via 2-way dip switch

Construction

- Steel body in white finish
- High quality opal diffuser to reduce glare
- Integral emergency option available
- Loop in/out mains connector
- BESA fixings for rear or end cable entry

Technical Data

General		Electrical	
Luminaire Wattage (W)	31 to 57	Rated Input Current (A)	0.26
Weight (kg)	1.43	Power Factor (pf)	0.89 to 0.96
Operating Temperature (ta °C)	45	Input Voltage Range (VAC)	220 to 240
Light Output		Inrush Current Peak (A)	200
Lumens (lm)	4200 to 7600	Surge Protection (kV)	L-N 1kV, LN-PG 2kV
Efficacy (lm/W)	146	Conductor Size (mm)	0.5 to 2.5
LED		Terminal Type	3 pole piano key
CRI	85		
Macadam Ellipses	5		
Driver			
Driver Current (mA)	200 , 250 , 300 , 350		
Forward Voltage (V)	80 to 172		
Emergency			
Emergency Lumen Operating	293		
Emergency Wattage (W)	2		

Order Code: XCBT5X1
BATTEN X1 CCT [3000K/4000K/6000K] + Wattage Switchable

Dimensions

A (mm)	1500
B (mm)	55
C (mm)	58
Fix	610

Line Drawing

