



Data Sheet

Product Code: MKP100

Product Description: 2-Way V-Com Push On/Off Rotary LED Dimmer 0-100W

Range: Replacement Module

Product Category: LED Dimmers

Barcode: 5021575003970

Dimensions: 52x26x42mm

Net Weight: 48g

Gross Weight: 50g

Fixing Centres: N/A

Depth from Mounting Face:

Recommended Back Box Depth: N/A

Operating Voltage: 230v 50Hz

Maximum Load Rating: LED: 100W

Maximum Current Rating: 0.4A

Terminal (Live) Diameter: 3.2mm; **Capacity:** 3 x 1.5mm²

Intended Applications: Indoor Use Only. Commercial & domestic lighting circuits including many dimmable LEDs.

Safety Advice: Not suitable for use with non-dimmable fluorescent bulbs and tubes, wire-wound or toroidal transformers or electric motors. Do not overload.

Applicable Safety Standard: BS EN 60669-2-1

Commodity Code: 85365005



Product Features

- ✔ Can be used to replace dimmer modules in existing faceplates or in the Matrix dimmer grid system
- ✔ V-Com intelligent TRIAC leading edge dimming technology
- ✔ Soft start feature and intelligent overload protection
- ✔ Adjustable minimum brightness setting and choice of driving modes to optimise the dimming performance of a given LED lighting load

All information is subject to change without notice. Errors and omissions excepted. Images are for illustrative purposes only. Individual features and colours may vary. Refer to date of issue to identify latest version.

Date of Issue: 25th March 2026 © Doyle & Tratt Products Ltd, Carylls Lea, Faygate, West Sussex, RH12 4SJ, United Kingdom. All rights reserved.