

DIE SELECTION GUIDE FOR HT51

Also applicable for RH50, RHM50**, HT51-KV, B500E, B500NDE, B500E-KV,
B550E & B550E-KV

Copper Tube Connectors

Copper Conductor sqmm Low str. Flex.		Connector		Hexagonal Crimp		Indent Crimp		
		Terminal Lug	Through Connector	Die Set	No. of Crimps*	Nest	Indentor	No. of Crimps*
4 - 6		A1-M	L1-M	ME1-50	1	MA1-50	PA1-50	1
10		A2-M A2-P12	L2-M	ME2-50	1	MA2.3-50	PA5-50	1
16		A3-M A3-P14	L3-M	ME3-50	1			1
25		A5-M A5-P16	L5-M	ME5-50	1	MA5-50		1
35	25 35	A7-M A7-P20	L7-M	ME7-50	1	MA7-50	PA10-50	1
	35	A9-M		ME9-50	1	MA9-50		1
50	50	A10-M A10-P25	L10-M	ME10-50	2	MA10-50		1
	50	A12-M		ME12-50	2	MA12-50	PA19-50	1
70	70	A14-M A14-P30	L14-M	ME14-50	2	MA14-50		1
	70	A17-M		ME17-50	2	MA17-50		1
95	95	A19-M	L19-M	ME19-50	2	MA19-50		1
	95	A20-M		ME20-50	2	MA20-50	1	
120	120	A24-M	L24-M	ME24-50	2	MA24-50	PA24-50	1
	120	A29-M		ME29-50	3			
150	150	A30-M	L30-M	ME30-50	3			
	150	A35-M		ME35-50	3			
185	185	A37-M	L37-M	ME37-50	3			
	185	A40-M		ME40-50 #	3			
240	240	A48-M	L48-M	ME48-50 #	3			
300	300	A60-M	L60-M	ME60-50 ♦	4			

Fits silver head versions only ♦ Only for B500E, B500NDE, B500E-KV, RH50 & RHM50

* No. of Crimps per end for Through Connectors

** Not suitable for Through Connectors

ABC Conductor Fittings

Die Set	Connector
M83-50	Various insulated fittings
M140-50	
M173-50	
M215-50	

Further assistance from Cembre Ltd

Tel: 01675 470440 Fax: 01675 470220 E-mail: sales@cembre.co.uk