

# Product datasheet

Specifications

**CLIPSAL**



Double Power Point Skin with 1 extra switch, Clipsal Iconic, Horizontal Mount, 250V, 10A, Clip-On

3025XC-XW

## Main

Range of product	Iconic
Range	Iconic
Product or component type	Skin
Colour tint	White (XW)
Type of packing	Polybag

## Complementary

Range compatibility	Iconic switched socket
Product destination	Switched socket
Device mounting	Flush
Number of rocker	3
Number of power socket outlets	2
Installation direction	Horizontal
Fixing mode	Clip-on
Surface finish	Matt
surface treatment	Untreated
Material	PC (polycarbonate): skin
Height	120 mm
Width	78 mm
Depth	12 mm
Net weight	0.02 kg

## Environment

Ambient air temperature for storage	0...60 °C
Ambient air temperature for operation	0...45 °C
Relative humidity	10...95 %

## Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	0.9 cm
Package 1 Width	7.8 cm

<b>Package 1 Length</b>	11.9 cm
<b>Package 1 Weight</b>	21.32 g
<b>Unit Type of Package 2</b>	BB1
<b>Number of Units in Package 2</b>	20
<b>Package 2 Height</b>	14.65 cm
<b>Package 2 Width</b>	10.2 cm
<b>Package 2 Length</b>	21.8 cm
<b>Package 2 Weight</b>	591 g

## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Environmental footprint

Carbon footprint (kg.eq.CO2 per CR, Total Life cycle) **10**

Environmental Disclosure [Product Environmental Profile](#)

## Use Better

### Materials and Substances

Recycled metal content at CR level **0**

Packaging made with recycled cardboard **Yes**

Packaging without single use plastic **No**

[EU RoHS Directive](#) **Compliant**

REACH Regulation [REACH Declaration](#)

## Use Again

### Repack and remanufacture

Circularity Profile **No need of specific recycling operations**

Take-back **No**