

DCM565P1-GB

18V XR BRUSHLESS 30CM CHAINSAW - 1 X 5AH

The DCM565 18V XR Compact Chainsaw is a versatile tool that can be used in either outdoor or construction applications. Featuring a 30cm Oregon Bar and Chain, the DCM565 is equally effective at cutting logs as it is trimming timber beams in confined spaces. Lightweight and easy to manoeuvre, the DCM565 benefits from a large auxiliary handle, auto-oiling and tool free bar and chain replacement. Delivering up to 70 cuts per charge on a 5Ah battery in 4x4” pressure treated spruce. With 1 X 5Ah battery and charger.

Selling Propositions

- 30cm TRI-LINK Bar and Chain covers twice it's length for fast completion on small to medium materials
- High efficiency Brushless motor, delivering up to 70 x 4x4” cuts of pressure treated spruce per charge using an 18V XR 5Ah battery
- Automatic oiling for reduced maintenance
- Tool free bar fitment and chain tensioning for fast chain adjustments
- Variable speed trigger so no pull starting is required together with improved control during cutting
- Chain speed of 7.68 m/s. plus a chain brake that stops in 1 second for improved safety
- Extensive overmould handle for extra grip and comfort in prolonged use

Standard Equipment

- DCB184 - 5Ah Battery (1)
- XR Multi-Voltage Charger (1)
- 30cm Bar and Chain (1)

Warranty specifications

- DEWALT 3 year European PT Guarantee (subject to registration)

Specifications	
Cut Capacity	30.0 cm
Bar length	30.0 cm
Chain Speed	7.7 m/s²
Oil-tank capacity	115.0 ml
Product Type	Chainsaw
Power Source	Cordless
Battery Type	Lithium-Ion
Battery Capacity	5 Ah
Battery Included	Yes
Power Rating	18.0 V
Safety lock off switch	Yes
Chain brake	Yes
Secondary handle	Yes
Chain brake time	<1
Pitch	3/8 "
Chain drive links	45.0
Auto-oiling	Yes
Weight	3.0 kg
Oil level window	Yes
Rear Hand Guard	Yes
Sound Pressure	76.5 dB(A)
Sound Power	96.5 dB(A)
Vibration	3.5 m/s²
Chain Pitch	3/8 "
Chain Gauge	0.05 "
Chain File	5.2 mm
No. of Chain Links	45.0
Motor Speed	3750-4200 rpm
Replacement Chain	DT20676