

<b>Dimmer:</b>	H-LEDITB100-GR	<b>Insert Code:</b>	1XLEDITB100 / LEDITB100
<b>Rating:</b>	5-100W (Halogen/Incandescent)	<b>Dimming Mode:</b>	Leading Edge / Trailing Edge
	5-100W (LED / 10 Lamps Max)		



LED Manufacturer	Description	Product Code	Wattage	Quantity Tested	Quality (0-5)	Additional Notes
All LED	GU10 Dimmable LED	AGU10007D	7W	1-10 LEDs	4	
All LED	GU10 Dimmable LED	AGU501D	5.5W	1-10 LEDs	4	
All LED	High Output COB GU10	AGU700D/30	7W	1-10 LEDs	4	
All LED	Cobra Fire-Rated LED Downlight	ACFD8/30	8W	1-10 LEDs	4	
All LED	350mA LED with All LED 14-25W Dimmable 350mA Driver	AGL060AL-30	7W	1-2 LEDs	4	
Aurora	MPRO Downlight	AU-MPRO	7W	1-10 LEDs	4	
Aurora	GU10 Dimmable LED	AU-DP208/27	8W	1-10 LEDs	5	Set minimum level
Aurora	GU10 Dimmable LED	AU-DGU107	7W	1-10 LEDs	5	
Aurora	i10 Downlight	AU-ALDD5010	10W	1-10 LEDs	4	
Aurora	M7 Downlight	AU-FRLD711	6W	1-10 LEDs	4	
Aurora	M5 Downlight	AU-FRLD511	5W	1-10 LEDs	4	Set minimum level
Bell	E27 Candle LED	05146	4W	1-10 LEDs	4	Better in Leading edge
Bell	Round Clear Ball LED	05188	4W	1-10 LEDs	4	Better in Leading edge
Bell	Fire Rated Downlight	08100	8W	1-6 LEDs	5	
Bell	6W GU10 LED		6W	1-8 LEDs	4	Better in Leading edge
Collingwood	H5 Trimless	DL282WHWWDIM	5.5W	1-10 LEDs	5	
Collingwood	Halers H2 Lite	DL388MW5530	5.8W	1-10 LEDs	5	
Collingwood	Halers H2 Pro 550	DL3566027	8.5W	1-10 LEDs	4	
Collingwood	Halers H2 Pro 700	DL2425530	11W	1-9 LEDs	4	
Enlite	E8 Downlight	EN-DE8	8W	1-10 LEDs	5	
Enlite	E5 Downlight	EN-DE5	5W	1-10 LEDs	5	
Enlite	GU10 Dimmable LED	EN-DGU005	5W	1-10 LEDs	4	
Enlite	GU10 Dimmable LED	EN-DGU005H	5W	1-10 LEDs	4	
Enlite	Fixed Round Integrated Downlight	EN-DDL1019	10W	1-10 LEDs	4	
Enlite	Fixed Round Integrated Downlight	EN-DDL1016	8W	1-10 LEDs	4	

Goodwin	GU10 Dimmable LED	GSP16G1005D/827	5W	1-10 LEDs	4	Better in Leading edge
JCC	Fire-Rated Downlight	FGLED6	6W	1-10 LEDs	4	
JCC	Fire-Rated Downlight	FGLED10	10W	2-9 LEDs	4	9 LEDs Max
JCC	Hybrid 7 Downlight	JC94701	7.2W	1-10 LEDs	4	Set minimum level
JCC	Hybrid 9 Downlight	JC94901	8.5W	1-10 LEDs	4	Set minimum level
JCC	V50 Downlight	JC1001	7.5W	1-10 LEDs	4	
KingShield	Dimmable Downlight	LEDDL3000K	9W	1-6 LEDs	4	
Kosnic	B22 Clear Candle	KDIM5.5CND/B22-SLV-N27	5.5W	1-10 LEDs	4	Set minimum level
KSR	GU10 Dimmable LED	KSRLP930	4.8W	1-10 LEDs	4	Better in Leading edge
KSR	Fire-Rated Downlight	KSRFRD262	8W	1-10 LEDs	4	
KSR	Firebreak QR4 LED Downlight	KSRFRD375	4.9W	1-10 LEDs	4	
KSR	Firebreak QR5 LED Downlight	KSRFRD373	5W	1-10 LEDs	4	
KSR	Firebreak QR10 LED Downlight	KSRFRD351	10W	1-10 LEDs	4	
LAP	GU10 Dimmable LED	LGDW5W37	5W	1-5 LEDs	5	
LEDVANCE	Spot Dim 3000K 620lm	Not Specified	8W	1-4 LEDs	4	
Lumilife	E14 Dimmable Candle	E14 5W	5W	1-10 LEDs	4	Set minimum level
Megaman	GU10 Dimmable LED	141490	6W	1-10 LEDs	4	Better in Leading edge
Megaman	GU10 Dimmable LED	141751	7W	1-10 LEDs	4	Better in Leading edge
Megaman	U-Dim LED Reflector GU10 PAR16	141324 (16W36)	5W	1-10 LEDs	4	
Megaman	U-Dim LED Reflector GU10 PAR16	141726 (16W36)	5.5W	1-10 LEDs	4	
Megaman	U-Dim LED Reflector GU10 PAR16	142202 (16W42)	7W	1-10 LEDs	4	
Megaman	Dim-to-warm GU10 PAR16	141806 (15W53)	6W	1-10 LEDs	4	
Megaman	E14 Clear Candle	143167	5W	1-10 LEDs	4	Better in Leading edge
Megaman	E14 Candle	143424	3.2W	1-6 LEDs	4	Use Leading Edge
Megaman	Dimmable Downlight	F29500RCv1-D Down Light	8W	1-10 LEDs	4	Set minimum level
Modo by Megaman	GU10 Dimmable LED	141317	5W	1-10 LEDs	4	Better in Leading edge
Osram	Parathom Advanced GU10	3W GU10	3W	1-10 LEDs	5	Set minimum level
Osram	Parathom Advanced GU10	7.2W GU10	7.2W	1-10 LEDs	4	
Osram	Parathom Advanced E14	E14 6W	6W	1-10 LEDs	4	
Save Light	Dimmable LED GU10	Halo-DF5W-4K	5W	1-6 LEDs	4	
Saxby	LED Downlight	73785	4W	1-5 LEDs	4	Set minimum level
Scolmore	Interceptor Micro	LED4300WH7CD	7.5W	1-10 LEDs	5	
Solo10	Dimmable LED Downlight	833839	10W	1-10 LEDs	4	

Steeple (Denmans)	Fire-Rated LED Downlight IP65 4000K	STLEDDL6CW	6W	1-10 LEDs	4	Set minimum level
Taison Lighting	Recessed Fire-Rated IP65 LED Downlight	T4GLB	13W	1-2 LEDs	5	

Third party lamps and bulbs specification may change. We try to test the latest version of the lamp available on testing date.