

Trimmer LXT®

DRT50RTJX2

18V • 6/8 mm

Light brushless manual trimmer with a wide range of accessories for carpentry

Handy trimmer for carpentry or hobbies. With the router trimmer, you can cut grooves or decorative trimmings in wood. Comes with 6 and 8 mm collets, guide rule, dust extraction adapter and edge milling and router modules. Wide range of blades. Equipped with an LED light.



Technical specifications

Voltage LXT	✓
Nominal Battery Voltage	18 V
Battery Chemistry (Ni-Cd / Ni-MH / Li-ion)	Li-ion
Max Output Power	800 W
No load speed	10000 - 30000 min ⁻¹
Max. Collet Capacity	0 - 1-3/8 "
Plunge capacity	0 - 40 mm
Plunge capacity with trimmer base	0 - 40 mm
Plunge capacity with plunge base	0 - 35 mm
Collet Capacity	6 / 8 mm
Sound Pressure Level (L _{pA})	78 dB(A)
Noise Uncertainty (K Factor)	3 dB(A)
Vibration Level, Cutting Grooves in MDF	4,5 m/s ²
Vibration Uncertainty (K Factor), Cutting Grooves in MDF	1,5 m/s ²

User benefits

- Brushless maintenance-free and long-life motor
- Battery protection system automatically shuts off power when the battery level is low

EAN 0088381846196

Link to product - www.makita.uk.com



Related products

Standard AC

153489-2
Grip complete 125 mm

122703-7
Trimmer Guide Assembly

194733-8
Dust nozzle set Ø 32 / 37 mm

195564-8
Guide Holder Set

126786-9
Tilt Base Assembly

 **195563-0**
Plunge base set

 **122965-7**
Straight guide assembly

 **195559-1**
Dust Nozzle

 **821552-6**
Makpac case (4)

450128-8 (2x)
Battery cover, LXT®, 14,4 – 18V



Standard MA

DC18RC
Battery Charger LXT®

 **BL1850B (2x)**
Battery LXT® 5,0 Ah



Optional AC

122391-0
Straight Guide

 **122703-7**
Trimmer Guide Assembly



122965-7
Straight guide assembly

 **153489-2**
Grip complete 125 mm



162258-0
Side Handle

 **164834-6**
Straight Guide



193312-9
Micro Adjustable Straight Guide

 **194367-7**
Guide rail, 3 000 mm



194385-5
Clamp set

 **194579-2**
Guide rail adapter



194733-8
Dust nozzle set Ø 32 / 37 mm

 **195559-1**
Dust Nozzle



195562-2
Offset base set

 **195563-0**
Plunge base set



195564-8
Guide Holder Set

 **198885-7**
Guide rail joint connector set, 2 pcs



198987-9
Router Tilt Base

 **199140-0**
Guide rail, 1 000 mm



Optional AC

199826-6

Quick-Release Ratcheting Guide Rail



343577-5

Templet Guide 8 x 10 x 9,5 mm



344364-5

Templet Guide 14,5 x 16 x 13 mm



763618-5

Collet cone 8 mm



763636-3

Collet cone 6 mm



781011-1

Wrench 22 mm



781039-9

Wrench 13



821552-6

Makpac case (4)



837247-1

MakPac (4) Inlay



B-57613

Guide rail bag



P-20177

Guide Rail Connector Set



Other

User manual

Parts drawing