

# CEP71EEDB

S+S CEP71 Overload Electronic Basic 3.2 to 16A for CA7 9 and 23A



Component type	Electronic overload relay
Range	CEP7 Gen 3
Model	N/A
Product status	Existing

The Sprecher + Schuh CEP7 Gen 3 Motor Overloads are the next generation basic-tier electronic overload relays. Accurately measuring a motor's current load and temperature, they can de-energise the motor minimising damage due to overheating. Featuring increased accuracy and repeatability, a self-powered design with lower heat dissipation, certifications and optional customisable accessory modules.

## ELECTRICAL

Adjustable current range	3.2-16 A
Release class	Adjustable
Max. rated operation voltage Ue	690 V
Number of auxiliary contacts as normally closed contact	1
Number of auxiliary contacts as normally open contact	1
Voltage type for actuating	Self powered
Reset function automatic	No
Reset function push-button	Yes
Type of electrical connection of main circuit	Screw connection

## CONSTRUCTION


Mounting method	Direct attachment
-----------------	-------------------

## DIMENSIONS

Height	86.6 mm
Width	44.8 mm
Depth	84.7 mm

## RELATED PRODUCTS

### ACCESSORY



**Item No:** CEP71BC8  
**Required:** No  
**Description:** S+S CEP71 Base Unit Anti Tamper Shield



**Item No:** CEP71EMRA  
**Required:** No  
**Description:** S+S CEP71 Reset Magnet 240VAC for CEP71

# CEP71EEDB

S+S CEP71 Overload Electronic Basic 3.2 to 16A for CA7 9 and 23A



MOTOR PROTECTION

sprecher+schuh

## RELATED PRODUCTS

### ACCESSORY



**Item No:** CEP71EMRD

**Required:** No

**Description:** S+S CEP71 Reset Magnet 120VAC for CEP71



**Item No:** CEP71EMRZ

**Required:** No

**Description:** S+S CEP71 Reset Magnet 24VDC for CEP71



**Item No:** CEP71EPB

**Required:** No

**Description:** S+S CEP71 Separate Mounting Adapter for CEP71 Frame B



**Item No:** CEP71ERA

**Required:** No

**Description:** S+S CEP71 External Reset Adapter