Product data sheet
Characteristics

LV431541
motor-mechanism - MT250 - SDE adaptor - 208..277 V 60Hz / 220..240 V 50/60Hz



Main

Range of product	Easypact CVS100...250 NSX100...250 DC NSX100...250 PowerPact multistandard
Range	Compact
Device short name	Motor mechanism module with SDE adaptor
Product or component-type	Motor mechanism
Device application	Automatic spring charging
Range compatibility	Compact - Compact NSX Compact - Compact NSX DC PowerPact Multistandard
Product compatibility	PowerPact H-Frame PowerPact J-Frame
[In] rated current	250 A
[Uc] control circuit voltage	208...277 V AC 60 Hz 220...240 V AC 50/60 Hz

Complementary

Control type	Standard
Control signal type	Maintained Impulse
Mounting mode	Fixed
Response time	< 600 ms - during opening time < 80 ms - during closing time
Maximum operating frequency	4 per minute
Power consumption in VA	<= 500 VA - during closing time <= 500 VA - during opening time
Provided equipment	SDE adaptor
Locking options description	1 to 3 padlocks Ø 5 to Ø 8 Padlocking in OFF position

Offer Sustainability

Sustainable offer status	Green Premium product
RoHS (date code: YYWW)	Compliant - since 0909 - Schneider Electric declaration of conformity Schneider Electric declaration of conformity
REACh	Reference not containing SVHC above the threshold
Product environmental profile	Available
Product end of life instructions	Available

Contractual warranty

Warranty period	18 months

Product Life Status : Commercialised

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein.
This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications.
It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof.
Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.