Data Sheet:

LG305





| Code | LG305 |
|-----------------------|--|
| | |
| Description | 8 way booster box with digital bypass & circuit protection |
| Size | 175 x 90 x 50mm |
| Range | Oxi-Gold Audio, Visual & Digital Accessories |
| Colour | Black |
| | |
| Included | Power Lead (Attached) Full instructions & mounting guide |
| Weight | 0.623kg |
| Inner Carton Quantity | 1 |
| | |
| Guarantee | 30 years |
| Barcode | 5025117986813 |
| Commodity Code | |
| Standards | BSEN60065:2002 |
| Notes | The quick, simple & safe way to boost / amplify your TV / FM signals Suitable for digital / Satellite / TV, Hi-Fi & DAB 100% appearance inspected & function tested before being released for sale Sturdy build & construction Frequency: VHF: 47-230MHz / UHF: 470-860MHz / FM: 88-108MHz Noise Figure: 3.5dB 220V/240V AC-50Hz Isolation Loss: 23dB Gain: 12 - 15dB For Indoor Use ONLY |