

Order Code: XCSEBAM3ST
XCITE EXIT BOX S ST 2W - 6500K - Fixed output - Emergency Self-test



Features

- Suitable for escape routes and exits
- Rear BESA fix and 3 additional rear fixing points
- Dual LED array for internal illumination and downward distribution
- Reduced maintenance and high performance
- Only 30mm depth for modern, slimline appearance
- Supplied with LiFePO4 battery

Construction

- Plastic body
- Hinged front lid for easy installation
- Supplied with universal EURO running man legend
- Integral auto self-test for reduced maintenance, includes a disable function



Technical Data

General		Electrical	
Luminaire Wattage (W)	2	Rated Input Current (A)	0.04
Weight (kg)	0.61	Power Factor (pf)	0.18
Operating Temperature (ta °C)	5° to 25°	Input Voltage Range (VAC)	220 to 240
Driver		Conductor Size (mm)	1.5
		Terminal Type	4 pole screw down
Driver Current (mA)	172		
Forward Voltage (V)	3.37		

Order Code: XCSEBAM3ST
XCITE EXIT BOX S ST 2W - 6500K - Fixed output - Emergency Self-test

Dimensions

A (mm)	325
B (mm)	185
C (mm)	30

Line Drawing

